



85648175



IP20

quicklink

HBNet F-TA 4k LI GRUTA K1 ANTH MATT

Technische Merkmale

Functions

- ETS additional functions: +6 scenes, 1 button control up/down, operating mode on/off, dimming value, brightness display, push-button, status display, forced control
- Functions for the push-button operation areas up/down or left/right can be freely configured as receiver for controlling the connected load and as transmitter for remote control of a blind, for example
- reset function (to factory setting)
- Configurable transmission and/or reception behaviour
- scene saving lockable
- quicklink functions: switching, dimming, blind, 2 scenes, time switching, NO contact push-button, memory

Controls and indicators

- operating areas configurable as one or two-area operation
- with configuration and function button

Connectivity

Radio protocol	KNX Radio
Receiver category	2

Frequency

Radio transmission/reception frequency	868,3 MHz
--	-----------

Power

Radio transmission power	< 10 mW
- low intrinsic energy requirement	

Measurement

Relative humidity (without condensation)	0 ... 65 % (without condensation)
--	-----------------------------------

Materials

RAL colour	RAL 7021 - Black grey
Colour of design line	anthracite
Material / workmanship	lacquered
Material	thermoplastic
Surface appearance	matt

LED control

- with configuration and function LEDs
- LED application module/insert compatibility display

Connection

- integration in the KNX radio/TP gateway, surface-mounted, into the KNX TP system

Settings

- toolless quicklink configuration using buttons and LED display

Equipment

Number of radio channels	4
Number of quicklink links	max. 20 transmitter/receiver
Transmitter duty cycle	1 %

- switch-on brightness level for each operating area on configuration with dimmer insert, power failure proof, storable

Safety

-
- with dismantling protection
-

Use conditions

Operating temperature	-5 ... 45 °C
-----------------------	--------------

Identification

Application, usage	Light control, KNX radio- operating systems
Secondary design line(s)	Berker.Net, Berker K.1

Instructions

-
- Extended operating options on 1 gang inserts through 2 additional, freely-configurable radio channels.
-