

16mm²

with screw



HAB406

## Load break switch 4P 63A

Product Datasheet

rch		

Connection

Type of connection

Connection cross-sect. rigid cable

Architecture	
Type of order	Short thumb-grip
Number of poles	4 P
Type of pole	4 P
Type of case	Fixed built-in
Functions	
Reversing switch	no
Controls and indicators	
Motor drive integrated	no
Main electrical features	
Rated operational voltage Ue	380 / 415 V
Frequency	50 Hz
Voltage	
Rated insulation voltage	800 V
Rated impulse withstand voltage	8000 V
Electric current	
Rated operational current in AC21category B	63 A
Acceptable current rating with AC22 category A	63 A
Rated current	63 A
Short-circuit current with gl-gG fuses	50 kA
Rated short-time withstand current 1s	1,26 kA
Rated operational current in AC21 category A	63 A
Acceptable current rating with AC22 category B	63 A
Rated operational current in AC23 category A	40 A
Acceptable current rating with AC23 category B	40 A
Power	
Total power loss under IN	9,6 W
Power loss per pole at In	2,4 W
Contact rating with 400 V in AC1	41 kW
Cover, door	
Interlockable	yes



## Equipment Motor drive optional no Standards Standard text IEC 60947-3 European directive WEEE concerned Safety Protection index IP IP20 Use conditions Operating temperature -20...70 °C